

**LED**  
TECHNOLOGY

50000 Hours, 36Watt, 120/270V, 60Hz, 4000Kelvin

**Dual Function: Use with fluorescent ballast or direct power connection 120-277VAC**

**Applications:**

8FT Strip light fixtures, 8FT sinage, Ceiling fixture

**Features:**

- Can be operated in luminaire with or without diffuser
- Dual mode internal driver plug and play to most ballasts (type A) or direct connect to line voltage 120-277VAC (type B)
- Come as 2-four foot sections couples in the centre to full a 96"
- Clear cupling in the center of the lamp give seamless light
- Includes magnetic clip for the lamp center, holds lamp securiyy on to the fixture


**Accesories:**

RH7D Conversion to Dual Pin, Cap Kit Available



**Specification:**

Input Line Voltage:.....	Ballast or 120/277VAC
Bare Lamp Power.....	36W
Input Line Frequency.....	50/60Hz
Lamp Life (Rated).....	50,000hrs
Minimum Starting Temp Preferred.....	-20°C/-4°F
Maximum Operating Temp Preferred.....	50°C/124°F
CCT.....	4000K
CRI.....	≥80
Lumens.....	5000
Beam Angle.....	200°



**WARRANTY**  
**5-YEARS** \*

Model:#	Description	Bare Lamp Wattage	Lumens	Pin Base
LB96T8-PNP/840	96" T8 FA8 Single Pin Plug-N-Play or Connect to 120-277VAC Direct Wire use, Cool white	36W	5000	G13+FA8

\*5 Years Limited Warranty

Model:LB96T8-PNP/840 UPC: 806802-155913

Accessory RH7D cap Model:FP96T82PCAP UPC: 806802-156033

